

## PRODUCTION POWER

### **STAGE LEFT (SOUND)**

- 1 X 100A 3PH SUPPLY ON 1 X 125A 3PH CEEFORM - 30mA 60ms RCD (NO TAILS)
- 1 X 60A 1PH SUPPLY ON 1 X 63A 1PH CEEFORM – 30mA RCD (NO TAILS)
- 1 X 32A 3PH CEEFORM FED FROM STAGE RIGHT 32A 3PH SUPPLY

### **STAGE RIGHT (LIGHTS/MOTORS)**

200A 3PH SUPPLY SPLIT INTO:

- 4 X 32A 1PH SUPPLIES ON 4 X 32A 1PH CEEFORM - 30mA RCD (NO TAILS)
- 1 X 200A 3PH SUPPLY ON 1 X POWERLOCK 30mA 60ms RCD (NO TAILS, BUT WE CAN PROVIDE AN ADAPTER TO CAMLOCK OR 125A 3PH CEEFORM)
- 1 X 32A 3PH CEEFORM FED FROM ABOVE 200A SUPPLY

ALL STAGE SUPPLIES ARE LESS THAN 5M FROM STAGE

### **AUDITORIUM**

- 6 X 63A 1PH SUPPLIES ON 63A CEEFORM (FED FROM S/R 200A 3PH SUPPLY)
- 1 X 32A 1PH CEEFORM (REAR OF HALL)

### **CAR PARK**

- 100A 3PH SUPPLY FEEDING 6 X 16A 1PH CEEFORM - 20mA RCD & 1 X 63A 3PH CEEFORM

### **FOYER EXTERIOR ROOF**

- 2 X 32A 3PH CEEFORM

### **MAINS DISTRO**

- 1 X 125A 3PH CEEFORM > 3 X 125A 1PH CEEFORM  
3 X 63A 1PH CEEFORM  
1 X 400A 3PH CAMLOK  
2 X 63A 3PH CEEFORM
- 6 X 63A 1PH CEEFORM > 2 X 32A 1PH CEEFORM  
2 X 16A 1PH CEEFORM  
2 X 13A SOCKET
- 2 X 63A 1PH CEEFORM > 2 X 32A 1PH CEEFORM
- 1 X 63A 3PH CEEFORM > 2 X 32A 3PH CEEFORM
- 1 X 32A 3PH CEEFORM > 4 X 16A 1PH CEEFORM
- 1 X 32A 3PH CEEFORM > 3 X 32A 1PH CEEFORM
- 5 X 32A 1PH CEEFORM > 3 X 16A 1PH CEEFORM
- 4 X 32A 1PH CEEFORM > 6 X 13A SOCKET
- 1 X POWERLOCK SPLITTER RACK 1 IN > 2 OUT

### **CABLE OVERVIEW**

- 1 X 5M 63A > 63A 1PH
- 6 X 10M 63A > 63A 1PH
- 2 X 50M 63A > 63A 1PH
- 1 X 3M, 5M & 10M POWERLOCK > POWERLOCK (FEEDING HOUSE DIMMER RACKS 1&2)
- 1 X 1M POWERLOCK > CAMLOK
- 1 X 0.5M POWERLOCK > 125A 3PH SOCKET
- 1 X 5M 125A 3PH CEEFORM > 125A 3PH CEEFORM

*VARIOUS OTHER 13, 15, 16, & 32A SINGLE PHASE CABLES AVAILABLE*

**SUBJECT TO CHANGE - ADDITIONAL POWER BY PRIOR ARRANGEMENT ONLY**

